```
% Tune-Up Tuesday #9 for November 6, 2018
```

```
% For the following linear time-invariant (LTI) filter observed for n >= 0, % y[n] = 0.9 \text{ y}[n-1] + (1/2) \text{ x}[n] + (1/2) \text{ x}[n-1] % We can move the term 0.9 \text{ y}[n-1] to the left-hand side: % y[n] - 0.9 \text{ y}[n-1] = (1/2) \text{ x}[n] + (1/2) \text{ x}[n-1] %
```

% Take z-transform of both sides. All initial conditions are zero to satisfy LTI properties.

% i. Plot the poles and zeros in the z domain.

```
feedforwardCoeffs = [ 1/2 1/2 ];
feedbackCoeffs = [ 1 -0.9 ];
figure;
zplane(feedforwardCoeffs, feedbackCoeffs);
```

- % *Answer:* The transfer function in the z-domain has a zero at z = -1 and pole at z = 0.9.
- % The pole has radius 0.9 and angle 0 rad/sample. If the pole were considered by itself,
- % then the filter would pass low frequencies (centered at the angle of the pole) and
- % attenuate high frequencies. The zero is on the unit circle at angle pi rad/sample,
- % which causes more attenuation in high frequencies. *Lowpass filter*.
- % Magnitude response at discrete-time frequency w would be the distance from a point
- % on the unit circle at $z = \exp(j w)$ to the zero location divided by the distance from the
- % point on the unit circle to the pole location, multiplied by the filter gain (1/2).

% ii. Plot the magnitude response in linear units over the interval –pi <= w <= pi.

When freqz is called without any return values, it would plot the phase response as well as the magnitude response in dB using $A_{dB} = 20 \log_{10} |A|$:

```
% |A| A_{dB} |A| A_{dB} |A| A_{dB} % 1.0 0dB 0.5 -6dB 0.0 -infinity
```

Below, we ask freqz to return the values calculated for the frequency responseand then plot the magnitude response in linear units instead of using deciBels.

```
W = -pi : 0.001 : pi;
[H, W] = freqz( feedforwardCoeffs, feedbackCoeffs, W );
figure;
plot(W, abs(H));
```

% Answer: Magnitude response peaks at 10 at 0 rad/sample and then decreases
 % to zero as the discrete-time frequency increases from 0 to pi. Lowpass filter.

% iii. Frequency selectivity?

%

%

- % Lowpass, highpass, bandpass, bandstop, allpass, notch. *Lowpass filter*.
- % Plots are on the next page.



