

$$y[n] = x[n] * h[n]$$

$$y[n] = \sum_{m=-\infty}^{\infty} h[m] x[n-m]$$

$$|y[n]| = \left| \sum_{m=-\infty}^{\infty} h[m] x[n-m] \right|$$

$$\leq \sum_{m=-\infty}^{\infty} |h[m] x[n-m]|$$

$$= \sum_{m=-\infty}^{\infty} |h[m]| |x[n-m]|$$

Since $|x[n]| \leq B_1$,

$$|y[n]| \leq B_1 \sum_{m=-\infty}^{\infty} |h[m]|$$

Derivation of

$$\sum_{n=-\infty}^{\infty} |h[n]| < \infty$$

condition

EE 313

Linear Systems and Signals

Prof. Brian L. Evans

Spring 2014

Bounded-Input
Bounded-Output
Stability of a
Linear Time-Invariant
System. Let input
 $|x[n]| \leq B_1$ for all n .

Special case: FIR Filter that has M coefficients.

$$\sum_{m=-\infty}^{\infty} |h[m]| = \sum_{m=0}^{M-1} |h[m]| < \infty$$

provided $|h[m]| < \infty$ for all m